

# **DRAFT TANZANIA STANDARD**

(Draft for comments only)

DC Power supply for notebook computers

en of s TANZANIA BUREAU OF STANDARDS w Alt for

This draft Tanzania Standard is being prepared by the Telecommunications and Information Technology Technical Committee, under the supervision of the Electrotechnical divisional standards committee (EDC)

This draft Tanzania Standard is an adoption of the International Standard **IEC 62700:2014** *DC Power supply for notebook computers,* Which has been prepared by the International Electrotechnical Commission

## 2 Terminology and conventions

Some terminologies and certain conventions are not identical with those used in Tanzania standards; attention is drawn especially to the following: -

- 1) The comma has been used as a decimal marker for metric dimensions. In Tanzania Standards, it is current practice to use "full point" on the baseline as the decimal marker.
- 2) Where the words "International Standard(s)" appear, referring to this standard they should read "Tanzania Standard(s)".



Edition 1.0 2014-02



Warning! Make sure that you obtained this publication from an authorized distributor.

## CONTENTS

INTRODUCTION.       6         1 Scope       7         2 Normative references       7         3 Terms, definitions and abbreviations       8         3.1 Terms and definitions       8         3.2 Abbreviations       8         4 Electrical specification (performance characteristics)       9         4.1 AC input rating       9         4.2 Inrush current       9         4.3 DC output toad condition and voltage regulation       9         4.4 DC output ripple and noise       9         4.5 Output transient response and capacitor load       9         4.6.1 Turn on delay time       9         4.6.2 Hold-up time       9         4.6.3 Rise time of output voltage       9         4.7.1 Over-current protection       10         4.7.1 Over-current protection       10         4.7.2 Short-circuit protection       10         5 DC power supply identification and computation method for notebook computers       10         6 Connectors for DC power supply ranoebook computer       12         6.1 General       13         6.2.2 Shape and dimension of DC connectors       13         6.3.4 General       13         6.3.5 General       13         6.3.6 General       13 </th <th>FC</th> <th colspan="7">FOREWORD</th>	FC	FOREWORD						
1       Scope       7         2       Normative references       7         3       Terms, definitions and abbreviations       8         3.1       Terms and definitions.       8         3.2       Abbreviations       8         4       Electrical specification (performance characteristics)       9         4.1       AC input rating       9         4.2       Inrush current       9         4.3       DC output load condition and voltage regulation       9         4.4       DC output traing tresponse and capacitor load       9         4.5       Output trains int response and capacitor load       9         4.6.1       Turn on delay time       9         4.6.2       Hold-up time       9         4.6.3       Rise time of output voltage       9         4.7       Protection       10         4.7.1       Over-current protection       10         4.7.2       Short-circuit protection       10         4.8       Over shoot       10         5       DC power supply identification and commobalion method for notebook computers       10         6       Connectors for DC power supply reprotection of DC connectors       13         6.2.1	IN	TRODU	CTION	6				
2       Normative references       7         3       Terms, definitions and abbreviations       8         3.1       Terms and definitions       8         3.1       Terms and definitions       8         3.2       Abbreviations       8         4       Electrical specification (performance characteristics)       9         4.1       AC input rating       9         4.2       Inrush current       9         4.3       DC output load condition and voltage regulation       9         4.4       DC output ringle and noise       9         4.5       Output transient response and capacitor load       9         4.6.1       Turn on delay time       9         4.6.2       Hold-up time       9         4.6.3       Rise time of output voltage       9         4.7       Protection       10         4.7.2       Short-circuit protection       10         4.7.2       Short-circuit protection       10         4.7.2       Short-circuit protection       10         4.6.3       Over shoot       10         5       Dc power supply identification and commodication method for notebook       10         6       Connectors for DC power supply removeb	1	Scope	Э	7				
3       Terms, definitions and abbreviations       8         3.1       Terms and definitions       8         3.2       Abbreviations       8         4       Electrical specification (performance characteristics)       9         4.1       AC input rating       9         4.2       Inrush current       9         4.3       DC output load condition and voltage regulation       9         4.4       DC output ripple and noise       9         4.5       Output transient response and capacitor load       9         4.6       Power supply timing       9         4.6.1       Turn on delay time       9         4.6.2       Hold-up time       9         4.6.3       Rise time of output voltage       9         4.7       Protection       10         4.7.1       Over-current protection       10         4.7.2       Short-circuit protection       100         4.8       Over shoot       10         5       DC power supply tight on otebook computer       12         6.1       General       13         6.2.2       Specification for DC connectors       13         6.2.3       Votage polarity and electrical specification of DC connectors	2	Norm	ative references	7				
3.1       Terms and definitions	3	Term	Terms, definitions and abbreviations					
3.2       Abbreviations       8         4       Electrical specification (performance characteristics)       9         4.1       AC input rating       9         4.2       Inrush current       9         4.3       DC output load condition and voltage regulation       9         4.4       DC output ripple and noise       9         4.5       Output transient response and capacitor load       9         4.6       Power supply timing       9         4.6.1       Turn on delay time       9         4.6.2       Hold-up time       9         4.6.3       Rise time of output voltage       9         4.7       Protection       10         4.7.1       Over-current protection       10         4.7.2       Short-circuit protection       10         4.7.2       Short-circuit protection       10         5       DC power supply identification and commodeation method for notebook computers       10         6       Connectors for DC power supply rot protebook computer       12         6.1       General       12         6.2       Specification for DC connectors       13         6.2.1       General       13         6.3       Cable qualues<		3.1	Terms and definitions	8				
4       Electrical specification (performance characteristics)       9         4.1       AC input rating       9         4.2       Inrush current       9         4.3       DC output load condition and voltage regulation       9         4.4       DC output inple and noise       9         4.5       Output transient response and capacitor load       9         4.6       Power supply timing       9         4.6.1       Turn on delay time       9         4.6.2       Hold-up time       9         4.6.3       Rise time of output voltage       9         4.7       Protection       10         4.7.1       Over-current protection       10         4.7.2       Short-circuit protection       10         4.7       Protection       10         5       DC power supply identification and commodeation method for notebook computer       10         6       Connectors for DC power supply ro notebook computer       12         6.1       General       12         6.2       Specification for DC connectors       13         6.2.2       Space and dimension of DC connectors       13         6.3.1       General       13         6.3.2       Specia		3.2	Abbreviations	8				
4.1       AC input rating       9         4.2       Inrush current       9         4.3       DC output ripple and noise       9         4.4       DC output ripple and noise       9         4.5       Output transient response and capacitor load       9         4.6       Power supply timing       9         4.6.1       Turn on delay time       9         4.6.2       Hold-up time       9         4.6.3       Rise time of output voltage       9         4.7       Protection       10         4.7.1       Over-current protection       10         4.7.2       Short-circuit protection       10         4.7.3       Short-circuit protection       10         4.7       Protection       10         5       DC power supply identification and commonication method for notebook computers       10         6       Connectors for DC power supply for probebook computer       12         6.1       General       12         6.2       Specification far DC connectors       13         6.2.2       Shape and dimension of DC connectors       13         6.3.1       General       13         6.3.2       Special considerations for an AC adapter with r	4	Electric	al specification (performance characteristics)	9				
4.2       Inrush current       9         4.3       DC output load condition and voltage regulation       9         4.4       DC output trapile and noise       9         4.4       DC output transient response and capacitor load       9         4.6       Power supply timing       9         4.6.1       Turn on delay time       9         4.6.2       Hold-up time       9         4.6.3       Rise time of output voltage       9         4.7       Protection       10         4.7.2       Short-circuit protection       10         5       DC power supply identification and commonication method for notebook computers       10         6       Connectors for DC power supply reprotebook computer       12         6.1       General       13         6.2.1       General       13         6.3.2       Special considerations for an AC adapter with replaceable cable       13         6.3.3       Gaberatal       13         6.3.4 <td></td> <td>4.1</td> <td>AC input rating</td> <td>9</td>		4.1	AC input rating	9				
4.3       DC output load condition and voltage regulation       9         4.4       DC output ripple and noise       9         4.5       Output transient response and capacitor load       9         4.6       Power supply timing       9         4.6.1       Turn on delay time       9         4.6.2       Hold-up time       9         4.6.3       Rise time of output voltage       9         4.6.1       Turn on delay time       9         4.6.2       Hold-up time       9         4.6.3       Rise time of output voltage       9         4.7       Protection       10         4.7.1       Over-current protection       10         4.7.2       Short-circuit protection       10         5       DC power supply identification and common eation method for notebook computers       10         6       Connectors for DC power supply no notebook computer       12         6.1       General       13         6.2.1       General       13         6.2.2       Shape and dimension of DC connectors       13         6.3.1       General       13         6.3.2       Special considerations for an AC adapter with replaceable cable       13         6.3.1 <td></td> <td>4.2</td> <td>Inrush current</td> <td>9</td>		4.2	Inrush current	9				
4.4       DC output ripple and noise       9         4.5       Output transient response and capacitor load       9         4.6       Power supply timing       9         4.6.1       Turn on delay time       9         4.6.2       Hold-up time       9         4.6.3       Rise time of output voltage       9         4.7       Protection       10         4.7.1       Over-current protection       10         4.7.2       Short-circuit protection       10         4.7.2       Short-circuit protection       10         4.8       Over shoot       10         5       DC power supply identification and communication method for notebook computers       10         6       Connectors for DC power supply for notebook computer       12         6.1       General       12         6.2       Specification for DC connectors       13         6.2.1       General       13         6.2.2       Shape and dimension of DC connectors       13         6.3.1       General       13         6.3.2       Special considerations for an AC adapter with replaceable cable       13         6.3.3       General       13         6.3.4       General		4.3	DC output load condition and voltage regulation	9				
4.5       Output transient response and capacitor load       9         4.6       Power supply timing       9         4.6.1       Turn on delay time       9         4.6.2       Hold-up time       9         4.6.3       Rise time of output voltage       9         4.7       Protection       10         4.7.1       Over-current protection       10         4.7.2       Short-circuit protection       10         4.8       Over shoot       10         5       DC power supply identification and communication method for notebook computers       10         6       Connectors for DC power supply for notebook computer       12         6.1       General       12         6.2       Specification for DC connectors       13         6.2.1       General       13         6.2.2       Shape and dimension of DC connectors       13         6.3.1       General       13         6.3.2       Special considerations for an AC adapter with replaceable cable       13         6.3.4       General       13         6.3.5       General       13         6.3.6       General       12         7       Achoc activities       16		4.4	DC output ripple and noise	9				
4.6       Power supply timing       9         4.6.1       Turn on delay time       9         4.6.2       Hold-up time       9         4.6.3       Rise time of output voltage       9         4.6.7       Protection       10         4.7.7       Protection       10         4.7.1       Over-current protection       10         4.7.2       Short-circuit protection       10         4.8       Over shoot       10         5       DC power supply identification and communication method for notebook computers       10         6       Connectors for DC power supply for notebook computer       12         6.1       General       13         6.2.2       Specification for DC connectors       13         6.3.1       General       13         6.3.2       Special considerations for an AC adapter with replaceable cable       13         6.3.3       Cable qualities       13         6.3.4       General       13         6.3.5       Special considerations for an AC adapter with replaceable cable       13         6.3.4       General       13         6.3.5       Special considerations for an AC adapter with replaceable cable       13         6.3.6 </td <td></td> <td>4.5</td> <td>Output transient response and capacitor load</td> <td>9</td>		4.5	Output transient response and capacitor load	9				
4.6.1       Turn on delay time       9         4.6.2       Hold-up time       9         4.6.3       Rise time of output voltage       9         4.7       Protection       10         4.7.1       Over-current protection       10         4.7.2       Short-circuit protection       10         4.7.3       Short-circuit protection       10         4.7.4       Over shoot       10         5       DC power supply identification and common bettion method for notebook computers       10         6       Connectors for DC power supply for notebook computer       12         6.1       General       12         6.2       Specification for DC connectors       13         6.2.1       General       13         6.2.2       Shape and dimension of DC connectors       13         6.3.1       General       13         6.3.2       Special considerations for an AC adapter with replaceable cable       13         6.3.3       General       13         6.3.4       General       13         6.3.5       Special considerations for an AC adapter with replaceable cable       13         6.3.1       General       13         6.3.2       Special considera		4.6	Power supply timing	9				
4.6.2       Hold-up time       9         4.6.3       Rise time of output voltage       9         4.7       Protection       10         4.7.1       Over-current protection       10         4.7.2       Short-circuit protection       10         4.8.3       Over shoot       10         5       DC power supply identification and communication method for notebook computers       10         6       Connectors for DC power supply for notebook computer       12         6.1       General       12         6.2       Specification for DC connectors       13         6.2.1       General       13         6.2.2       Shape and dimension of DC connectors       13         6.3       Cable qualities       13         6.3.1       General       13         6.3.2       Special considerations for an AC adapter with replaceable cable       13         6.3.1       General       13         6.3.2       Special considerations for an AC adapter with replaceable cable       13         6.3.4       General       13         6.3.5       General       13         6.3.6       Cable qualities       16         6.3.1       General       13		4.6.1	Turn on delay time	9				
4.6.3       Rise time of output voltage       9         4.7       Protection       10         4.7.1       Over-current protection       10         4.7.2       Short-circuit protection       10         4.7.3       Over shoot       10         5       DC power supply identification and communication method for notebook computers       10         6       Connectors for DC power supply for notebook computer       12         6.1       General       12         6.2       Specification far DC connectors       13         6.2.1       General       13         6.2.2       Shape and dimension of DC connectors       13         6.3.1       General       13         6.3.2       Special considerations for an AC adapter with replaceable cable       13         6.3.2       Special considerations for an AC adapter with replaceable cable       13         6.3.2       Special considerations for an AC adapter with replaceable cable       13         6.3.2       Special considerations for an AC adapter with replaceable cable       13         6.3.2       Special considerations for an AC adapter with replaceable cable       14         Annex A (normative)       Act adapters used with notebook computers – Areas to be investigated       20		4.6.2	Hold-up time	9				
4.7       Protection       10         4.7.1       Over-current protection       10         4.7.2       Short-circuit protection       10         4.7.2       Short-circuit protection       10         4.8       Over shoot       10         5       DC power supply identification and commonication method for notebook computers       10         6       Connectors for DC power supply for notebook computer       12         6.1       General       12         6.2       Specification for DC connectors       13         6.2.1       General       13         6.2.2       Shape and dimension of DC connectors       13         6.2.3       Voltage polarity and electrical specification of DC connectors       13         6.3.1       General       13         6.3.2       Special considerations for an AC adapter with replaceable cable       13         6.3.3       General       13         6.3.4       Informative)       Ad-hoc activities       16         Annex A (informative)       Ad-hoc activities       16         Annex D (informative)       AC adapters used with notebook computers – Areas to be investigated       20         C.1       Safety       20       20         C		4.6.3	Rise time of output voltage	9				
4.7.1       Over-current protection       10         4.7.2       Short-circuit protection       10         4.8       Over shoot       10         5       DC power supply identification and communication method for notebook computers       10         6       Connectors for DC power supply for notebook computer       12         6.1       General       12         6.2       Specification for DC connectors       13         6.2.1       General       13         6.2.2       Shape and dimension of DC connectors       13         6.3.1       General       13         6.2.2       Shape and dimension of DC connectors       13         6.3.1       General       13         6.3.2       Voltage polarity and electrical specification of DC connectors       13         6.3.1       General       13         6.3.2       Special considerations for an AC adapter with replaceable cable       13         6.3.2       Special considerations for an AC adapter with replaceable cable       13         Annex A (normative)       Aumary of discussion in project team IEC 62700       14         Annex C (informative)       AC adapters used with notebook computers – Areas to be investigated       20         C.1       Safety		4.7	Protection	10				
4.7.2       Short-circuit protection       10         4.8       Over shoot       10         5       DC power supply identification and commonitation method for notebook computers       10         6       Connectors for DC power supply for notebook computer       12         6.1       General       12         6.2       Specification for DC connectors       13         6.2.1       General       13         6.2.2       Shape and dimension of DC connectors       13         6.2.3       Voltage polarity and electrical specification of DC connectors       13         6.3.1       General       13         6.3.2       Special considerations for an AC adapter with replaceable cable       13         6.3.1       General       13         6.3.2       Special considerations for an AC adapter with replaceable cable       13         6.3.2       Special considerations for an AC adapter with replaceable cable       13         Annex A (informative)       Ad-hoc activities       16         Annex B (informative)       Ad-hoc activities       20         C.1       Safety       20       20         C.2       EMC       20       20         C.3       Future trends in connectivity and power delivery       <		4.7.1	Over-current protection	10				
4.8       Over shoot       10         5       DC power supply identification and communication method for notebook computers       10         6       Connectors for DC power supply for notebook computer       12         6.1       General       12         6.2       Specification for DC connectors       13         6.2.1       General       13         6.2.2       Shape and dimension of DC connectors       13         6.3.2       Specifications for DC power supply and electrical specification of DC connectors       13         6.3       Cable qualities       13         6.3       Cable qualities       13         6.3.1       General       13         6.3.2       Special considerations for an AC adapter with replaceable cable       13         6.3.1       General       13         6.3.2       Special considerations for an AC adapter with replaceable cable       13         Annex A (informative)       Summary of discussion in project team IEC 62700       14         Annex C (informative)       Ad-hoc activities       16         Annex C (informative)       AC adapters used with notebook computers – Areas to be investigated       20         C.1       Safety       20       20         C.2       EMC		4.7.2	Short-circuit protection	10				
5       DC power supply identification and communication method for notebook computers       10         6       Connectors for DC power supply for notebook computer       12         6.1       General       12         6.2       Specification for DC connectors       13         6.2.1       General       13         6.2.2       Shape and dimension of DC connectors       13         6.2.3       Voltage polarity and electrical specification of DC connectors       13         6.3       Cable qualities       13         6.3.1       General       13         6.3.2       Special considerations for an AC adapter with replaceable cable       13         6.3.2       Special considerations for an AC adapter with replaceable cable       13         6.3.2       Special considerations for an AC adapter with replaceable cable       13         Annex A (Informative)       Summary of discussion in project team IEC 62700       14         Annex C (informative)       Ad-hoc activities       16         Annex C (informative)       AC adapters used with notebook computers – Areas to be investigated       20         C.1       Safety       20         C.3       Future trends in connectivity and power delivery       20         C.3       Future trends in connectivity and power		4.8	Over shoot	10				
computers       10         6       Connectors for DC power supply for notebook computer       12         6.1       General       12         6.2       Specification for DC connectors       13         6.2.1       General       13         6.2.2       Shape and dimension of DC connectors       13         6.2.3       Voltage polarity and electrical specification of DC connectors       13         6.3       Cable qualities       13         6.3.1       General       13         6.3.2       Special considerations for an AC adapter with replaceable cable       13         6.3.2       Special considerations for an AC adapter with replaceable cable       13         6.3.2       Special considerations for an AC adapter with replaceable cable       14         Annex A (informative)       Summary of discussion in project team IEC 62700       14         Annex C (informative)       AC adapters used with notebook computers – Areas to be investigated       20         C.1       Safety       20         C.2       EMC       20         C.3       Future trends in connectivity and power delivery       20         Annex D (informative)       Expected issues when any adapter is connected to any host       21         D.1       Safety iss	5	DC pow	ver supply identification and communication method for notebook	40				
6       Connectors for DC power supply for notebook computer       12         6.1       General       12         6.2       Specification for DC connectors       13         6.2.1       General       13         6.2.2       Shape and dimension of DC connectors       13         6.2.3       Voltage polarity and electrical specification of DC connectors       13         6.3       Cable qualities       13         6.3.1       General       13         6.3.2       Special considerations for an AC adapter with replaceable cable       13         6.3.2       Special considerations for an AC adapter with replaceable cable       13         6.3.2       Special considerations for an AC adapter with replaceable cable       14         Annex A (informative)       Summary of discussion in project team IEC 62700       14         Annex C (informative)       Ad-hoc activities       16         Annex C (informative)       AC adapters used with notebook computers – Areas to be       20         C.1       Safety       20         C.2       EMC       20         C.3       Future trends in connectivity and power delivery       20         Annex D (informative)       Expected issues when any adapter is connected to any host       21         <	_	comp	uters	10				
6.1       General       12         6.2       Specification for DC connectors       13         6.2.1       General       13         6.2.2       Shape and dimension of DC connectors       13         6.2.3       Voltage polarity and electrical specification of DC connectors       13         6.3.1       General       13         6.3.2       Special considerations for an AC adapter with replaceable cable       13         6.3.2       Special considerations for an AC adapter with replaceable cable       13         Annex A (normative)       Summary of discussion in project team IEC 62700       14         Annex B (informative)       Ad-hoc activities       16         Annex C (informative)       AC adapters used with notebook computers – Areas to be       20         C.1       Safety       20         C.2       EMC       20         C.3       Future trends in connectivity and power delivery       20         C.3       Future trends in connectivity and power delivery       20         C.1       Safety issues       21         D.1       Safety issues       21         D.1       Over-voltage protection       21         D.1.2       Over-current protection and short circuit protection       21	6	Connec	tors for DC power supply for notebook computer	12				
6.2       Specification for DC connectors       13         6.2.1       General       13         6.2.2       Shape and dimension of DC connectors       13         6.2.3       Voltage polarity and electrical specification of DC connectors       13         6.3       Cable qualities       13         6.3.1       General       13         6.3.2       Special considerations for an AC adapter with replaceable cable       13         6.3.2       Special considerations for an AC adapter with replaceable cable       13         Annex A (informative)       Summary of discussion in project team IEC 62700       14         Annex B (informative)       Ad-hoc activities       16         Annex C (informative)       AC adapters used with notebook computers – Areas to be       20         C.1       Safety       20         C.2       EMC       20         C.3       Future trends in connectivity and power delivery       20         C.3       Future trends in connectivity and power delivery       20         Annex D (informative)       Expected issues when any adapter is connected to any host       21         D.1       Safety issues       21       21         D.1       Over-voltage protection       21         D.1.2		6.1	General	12				
6.2.1       General       13         6.2.2       Shape and dimension of DC connectors       13         6.2.3       Voltage polarity and electrical specification of DC connectors       13         6.3       Cable qualities       13         6.3       Cable qualities       13         6.3       General       13         6.3.1       General       13         6.3.2       Special considerations for an AC adapter with replaceable cable       13         Annex A (Informative)       Summary of discussion in project team IEC 62700       14         Annex B (informative)       Ad-hoc activities       16         Annex C (informative)       Ad-hoc activities       16         Annex C (informative)       AC adapters used with notebook computers – Areas to be       20         C.1       Safety       20         C.2       EMC       20         C.3       Future trends in connectivity and power delivery       20         Annex D (informative)       Expected issues when any adapter is connected to any host         T       D.1       Safety issues       21         D.1.1       Over-voltage protection       21         D.1.2       Over-current protection and short circuit protection       21 <td></td> <td>6.2</td> <td>Specification for DC connectors</td> <td>13</td>		6.2	Specification for DC connectors	13				
6.2.2       Shape and dimension of DC connectors       13         6.2.3       Voltage polarity and electrical specification of DC connectors       13         6.3       Cable qualities       13         6.3.1       General       13         6.3.2       Special considerations for an AC adapter with replaceable cable       13         Annex A (informative)       Summary of discussion in project team IEC 62700       14         Annex B (informative)       Ad-hoc activities       16         Annex C (informative)       AC adapters used with notebook computers – Areas to be investigated       20         C.1       Safety       20         C.2       EMC       20         C.3       Future trends in connectivity and power delivery       20         C.3       Future trends in connectivity and power delivery       20         Annex D (informative)       Expected issues when any adapter is connected to any host       21         D.1       Safety issues       21         D.1.1       Over-voltage protection       21         D.1.2       Over-current protection and short circuit protection       21		6.2.1	General	13				
6.2.3       Voltage polarity and electrical specification of DC connectors       13         6.3       Cable qualities       13         6.3.1       General       13         6.3.2       Special considerations for an AC adapter with replaceable cable       13         Annex A (Informative)       Summary of discussion in project team IEC 62700       14         Annex B (informative)       Ad-hoc activities       16         Annex C (informative)       AC adapters used with notebook computers – Areas to be       20         C.1       Safety       20         C.2       EMC       20         C.3       Future trends in connectivity and power delivery       20         Annex D (informative)       Expected issues when any adapter is connected to any host       21         D.1       Safety issues       21         D.1.1       Over-voltage protection       21         D.1.2       Over-current protection and short circuit protection       21		6.2.2	Shape and dimension of DC connectors	13				
6.3       Cable qualities       13         6.3.1       General       13         6.3.2       Special considerations for an AC adapter with replaceable cable       13         Annex A (informative)       Summary of discussion in project team IEC 62700       14         Annex B (informative)       Ad-hoc activities       16         Annex C (informative)       AC adapters used with notebook computers – Areas to be       10         c.1       Safety       20         C.2       EMC       20         C.3       Future trends in connectivity and power delivery       20         Annex D (informative)       Expected issues when any adapter is connected to any host       21         D.1       Safety issues       21         D.1.1       Over-voltage protection       21         D.1.2       Over-current protection and short circuit protection       21		6.2.3	Voltage polarity and electrical specification of DC connectors	13				
6.3.1       General       13         6.3.2       Special considerations for an AC adapter with replaceable cable       13         Annex A (Informative)       Summary of discussion in project team IEC 62700       14         Annex B (informative)       Ad-hoc activities       16         Annex C (informative)       AC adapters used with notebook computers – Areas to be       16         Annex C (informative)       AC adapters used with notebook computers – Areas to be       20         C.1       Safety       20         C.2       EMC       20         C.3       Future trends in connectivity and power delivery       20         Annex D (informative)       Expected issues when any adapter is connected to any host       21         D.1       Safety issues       21         D.1.1       Over-voltage protection       21         D.1.2       Over-current protection and short circuit protection       21		6.3	Cable qualities	13				
6.3.2       Special considerations for an AC adapter with replaceable cable       13         Annex A (informative)       Summary of discussion in project team IEC 62700       14         Annex B (informative)       Ad-hoc activities       16         Annex C (informative)       Ad hoc activities       16         Annex C (informative)       AC adapters used with notebook computers – Areas to be       20         C.1       Safety       20         C.2       EMC       20         C.3       Future trends in connectivity and power delivery       20         Annex D (informative)       Expected issues when any adapter is connected to any host       21         D.1       Safety issues       21         D.1.1       Over-voltage protection       21         D.1.2       Over-current protection and short circuit protection       21		6.3.1	General	13				
Annex A (informative)       Summary of discussion in project team IEC 62700       14         Annex B (informative)       Ad-hoc activities       16         Annex C (informative)       AC adapters used with notebook computers – Areas to be       16         Annex C (informative)       AC adapters used with notebook computers – Areas to be       20         C.1       Safety       20         C.2       EMC       20         C.3       Future trends in connectivity and power delivery       20         Annex D (informative)       Expected issues when any adapter is connected to any host         *       21         D.1       Safety issues       21         D.1.1       Over-voltage protection       21         D.1.2       Over-current protection and short circuit protection       21		6.3.2	Special considerations for an AC adapter with replaceable cable	13				
Annex B (informative)       Ad-hoc activities	Ar	nnex A (I	nformative) Summary of discussion in project team IEC 62700	. 14				
Annex C (informative)       AC adapters used with notebook computers – Areas to be       20         C.1       Safety       20         C.2       EMC       20         C.3       Future trends in connectivity and power delivery       20         Annex D (informative)       Expected issues when any adapter is connected to any host       21         D.1       Safety issues       21         D.1.1       Over-voltage protection       21         D.1.2       Over-current protection and short circuit protection       21	Ar	nnex B (ii	nformative) Ad-hoc activities	. 16				
investigated       20         C.1       Safety       20         C.2       EMC       20         C.3       Future trends in connectivity and power delivery       20         Annex D (informative)       Expected issues when any adapter is connected to any host       21         D.1       Safety issues       21         D.1.1       Over-voltage protection       21         D.1.2       Over-current protection and short circuit protection       21	Ar	nnex C (i	nformative) AC adapters used with notebook computers – Areas to be	~ ~				
C.1       Safety       20         C.2       EMC       20         C.3       Future trends in connectivity and power delivery       20         Annex D (informative)       Expected issues when any adapter is connected to any host       21         D.1       Safety issues       21         D.1.1       Over-voltage protection       21         D.1.2       Over-current protection and short circuit protection       21		inves	tigated	20				
C.2       EMC       20         C.3       Future trends in connectivity and power delivery       20         Annex D (informative)       Expected issues when any adapter is connected to any host       21         D.1       Safety issues       21         D.1.1       Over-voltage protection       21         D.1.2       Over-current protection and short circuit protection       21		C.1	Safety	. 20				
C.3 Future trends in connectivity and power delivery		C.2	EMC	. 20				
21         D.1       Safety issues       21         D.1.1       Over-voltage protection       21         D.1.2       Over-current protection and short circuit protection       21	C.3 Future trends in connectivity and power delivery Annex D (informative) Expected issues when any adapter is connected to any host							
D.1Safety issues21D.1.1Over-voltage protection21D.1.2Over-current protection and short circuit protection21		PC		21				
D.1.1 Over-voltage protection		D.1	Safety issues	. 21				
D.1.2 Over-current protection and short circuit protection		D.1.1	Over-voltage protection	. 21				
		D.1.2	Over-current protection and short circuit protection	. 21				

D.1.4       Peak current.       21         D.1.5       Surge and ringing.       21         D.1.6       Surface temperature of enclosure of AC adapters.       21         D.1.7       Risk of electric shock.       21         D.2       EMC issues.       22         D.2.1       Load change       22         D.2.2       Input power circuit of PC       22         D.3       Environment issues.       22         D.3.1       Inrush current.       22         D.3.2       General specifications.       22         D.3.3       High-efficiency technology.       22         D.4.4       Reliability and quality issues.       22         D.4.1       Life time       22         D.4.2       Extraordinary noise.       23         D.5.1       Environments.       23         D.5.2       EMC evaluation       23         D.5.4       Safety evaluation.       23         D.5.5       LSr equirements       23         D.5.6       Pigu.       23         D.5.7       Marking of electrical specification       25         E.1       DC output load condition and voltage regulation       25         E.2       Over-cur	D.1.3	Leakage current	21
D.1.5       Surge and ringing.       21         D.1.6       Surface temperature of enclosure of AC adapters.       21         D.1.7       Risk of electric shock.       21         D.2       EMC issues.       22         D.2.1       Load change.       22         D.2.2       Input power circuit of PC.       22         D.3       Environment issues       22         D.3.1       Inrush current.       22         D.3.2       General specifications       22         D.3.3       High-efficiency technology       22         D.4       Reliability and quality issues       22         D.4.1       Life time       22         D.4.2       Extraordinary noise       23         D.5       Standards issues       23         D.5.1       Environments       23         D.5.3       EMC evaluation       23         D.5.4       Safety evaluation       23         D.5.5       LPS requirements       23         D.5.6       Plug       23         D.5.7       Marking of electrical ratings on PC       23         D.6       Other issues       24         Annex E (informative)       Electrical specification	D.1.4	Peak current	21
D.1.6       Surface temperature of enclosure of AC adapters.       .21         D.1.7       Risk of electric shock.       .21         D.2       EMC issues.       .22         D.2.1       Load change       .22         D.2.2       Input power circuit of PC       .22         D.3       Environment issues       .22         D.3.1       Inrush current       .22         D.3.2       General specifications       .22         D.3.3       High-efficiency technology       .22         D.4       Reliability and quality issues       .22         D.4.1       Life time       .22         D.4.2       Extraordinary noise       .23         D.5.4       Environments       .23         D.5.5       Isondards issues       .23         D.5.4       Environments       .23         D.5.5       LPS requirements       .23         D.5.4       Safety evaluation       .23         D.5.5       LPS requirements       .23         D.5.6       Plug       .23         D.5.7       Marking of electrical specification       .25         E.1       DC output load condition and voltage regulation       .25         E.2 <t< td=""><td>D.1.5</td><td>Surge and ringing</td><td>21</td></t<>	D.1.5	Surge and ringing	21
D.1.7       Risk of electric shock       21         D.2       EMC issues       22         D.2.1       Load change       22         D.2.2       Input power circuit of PC       22         D.3       Environment issues       22         D.3.1       Inrush current       22         D.3.2       General specifications       22         D.3.3       High-efficiency technology       22         D.4       Reliability and quality issues       22         D.4.1       Life time       22         D.4.2       Extraordinary noise       23         D.5       Standards issues       23         D.5.1       Environments       23         D.5.2       EMC evaluation       23         D.5.3       EMC class       23         D.5.4       Safety evaluation       23         D.5.5       LPS requirements       23         D.5.6       Plug       23         D.5.7       Marking of electrical ratings on PC       23         D.5.6       Plug       23         D.5.7       Do output load condition and voltage regulation       25         E.1       DC output load condition and voltage regulation       25	D.1.6	Surface temperature of enclosure of AC adapters	21
D.2       EMC issues       22         D.2.1       Load change       22         D.2.2       Input power circuit of PC       22         D.3       Environment issues       22         D.3.1       Inrush current       22         D.3.2       General specifications       22         D.3.3       High-efficiency technology       22         D.4       Reliability and quality issues       22         D.4.1       Life time       22         D.4.2       Extraordinary noise       23         D.5.5       Standards issues       23         D.5.4       Environments       23         D.5.5       EMC evaluation       23         D.5.4       Safety evaluation       23         D.5.5       LPS requirements       23         D.5.6       Plug       23         D.5.7       Marking of electrical ratings on PC       23         D.6       Other issues       24         Annex E (informative)       Electrical specification       25         E.1       DC output load condition and voltage regulation       25       25         E.2       Over-current protection       26         Bibliography       27	D.1.7	Risk of electric shock	21
D.2.1       Load change       22         D.2.2       Input power circuit of PC       22         D.3       Environment issues       22         D.3.1       Inrush current       22         D.3.2       General specifications       22         D.3.3       High-efficiency technology       22         D.4       Reliability and quality issues       22         D.4.4       Reliability and quality issues       23         D.5.5       Extraordinary noise       23         D.5.6       Extraordinary noise       23         D.5.1       Environments       23         D.5.2       EMC evaluation       23         D.5.4       Safety evaluation       23         D.5.5       LPS requirements       23         D.5.6       Plug       23         D.5.7       Marking of electrical ratings on PC       23         D.5.7       Marking of electrical specification       25         E.1       DC output load condition and voltage regulation       25         E.2       Over-current protection       26         Bibliography       27         Figure 1 – Shape of the plug       12         Figure B.1 – Radiateb emission       17	D.2	EMC issues	22
D.2.2       Input power circuit of PC	D.2.1	Load change	22
D.3       Environment issues       22         D.3.1       Inrush current       22         D.3.2       General specifications       22         D.3.3       High-efficiency technology       22         D.4       Reliability and quality issues       22         D.4       Reliability and quality issues       22         D.4.1       Life time       22         D.4.2       Extraordinary noise       23         D.5       Standards issues       23         D.5.1       Environments       23         D.5.2       EMC evaluation       23         D.5.3       EMC class       23         D.5.4       Safety evaluation       23         D.5.5       LPS requirements       23         D.5.6       Plug       23         D.5.6       Plug       23         D.5.7       Marking of electrical ratings on PC       23         D.6       Other issues       24         Annex E (informative)       Electrical specification       25         E.1       DC output load condition and outage regulation       25         E.2       Over-current protection       26         Bibliography       27	D.2.2	Input power circuit of PC	22
D.3.1       Inrush current	D.3	Environment issues	22
D.3.2       General specifications       22         D.3.3       High-efficiency technology       22         D.4       Reliability and quality issues       22         D.4       Reliability and quality issues       22         D.4       Reliability and quality issues       22         D.4.1       Life time       22         D.4.2       Extraordinary noise       23         D.5       Standards issues       23         D.5.1       Environments       23         D.5.2       EMC evaluation       23         D.5.3       EMC class       23         D.5.4       Safety evaluation       23         D.5.5       LPS requirements       23         D.5.6       Plug       23         D.5.7       Marking of electrical ratings on PC       23         D.5.6       Plug       23         D.5.7       Marking of electrical ratings on PC       23         D.6       Other issues       24         Annex E (informative)       Electrical specification       25         E.1       DC output load condition and voltage regulation       25         E.2       Over-current protection       26         Bibliography       <	D.3.1	Inrush current	22
D.3.3       High-efficiency technology	D.3.2	General specifications	22
D.4       Reliability and quality issues       22         D.4.1       Life time       22         D.4.2       Extraordinary noise       23         D.5       Standards issues       23         D.5.1       Environments       23         D.5.2       EMC evaluation       23         D.5.3       EMC class       23         D.5.4       Safety evaluation       23         D.5.5       LPS requirements       23         D.5.6       Plug       23         D.5.7       Marking of electrical ratings on PC       23         D.5.6       Plug       23         D.5.7       Marking of electrical ratings on PC       23         D.6       Other issues       24         Annex E (informative)       Electrical specification       25         E.1       DC output load condition and voltage regulation       25         E.2       Over-current protection       26         Bibliography       27       Figure 8.1 – Radiated emission       17         Figure B.1 – Radiated emission       18       19         Table 1 – Dimensions of the plug       12       12	D.3.3	High-efficiency technology	22
D.4.1       Life time       22         D.4.2       Extraordinary noise       23         D.5       Standards issues       23         D.5.1       Environments       23         D.5.2       EMC evaluation       23         D.5.3       EMC class       23         D.5.4       Safety evaluation       23         D.5.5       LPS requirements       23         D.5.6       Plug       23         D.5.7       Marking of electrical ratings on PC       23         D.6       Other issues       24         Annex E (informative)       Electrical specification       25         E.1       DC output load condition and voltage regulation       25         E.2       Over-current protection       26         Bibliography       27       Figure 1 – Shape of the plug       12         Figure B.1 – Radiated emission       18       18         Figure B.2 – Conducted emission       18       19         Table 1 – Dimensions of the plug       12	D.4	Reliability and quality issues	22
D.4.2       Extraordinary noise       23         D.5       Standards issues       23         D.5.1       Environments       23         D.5.2       EMC evaluation       23         D.5.3       EMC class       23         D.5.4       Safety evaluation       23         D.5.5       LPS requirements       23         D.5.6       Plug       23         D.5.7       Marking of electrical ratings on PC       23         D.6       Other issues       24         Annex E (informative)       Electrical specification       25         E.1       DC output load condition and voltage regulation       25         E.2       Over-current protection       26         Bibliography       27       12         Figure 1 – Shape of the plug       12         Figure B.1 – Radiated emission       17         Figure B.2 – Conducted emission       18         Figure B.3 – Conducted emission       19         Table 1 – Dimensions of the plug       12	D.4.1	Life time	22
D.5       Standards issues       23         D.5.1       Environments       23         D.5.2       EMC evaluation       23         D.5.3       EMC class       23         D.5.4       Safety evaluation       23         D.5.5       LPS requirements       23         D.5.6       Plug       23         D.5.7       Marking of electrical ratings on PC       23         D.6       Other issues       24         Annex E (informative)       Electrical specification       25         E.1       DC output load condition and voltage regulation       25         E.2       Over-current protection       26         Bibliography       27       12         Figure 1 – Shape of the plug       12         Figure B.1 – Radiated emission       17         Figure B.2 – Conducted emission       18         Figure B.3 – Conducted emission       19         Table 1 – Dimensions of the plug       12	D.4.2	Extraordinary noise	23
D.5.1       Environments       23         D.5.2       EMC evaluation       23         D.5.3       EMC class       23         D.5.4       Safety evaluation       23         D.5.5       LPS requirements       23         D.5.6       Plug       23         D.5.7       Marking of electrical ratings on PC       23         D.6       Other issues       24         Annex E (informative)       Electrical specification       25         E.1       DC output load condition and voltage regulation       25         E.2       Over-current protection       26         Bibliography       27       12         Figure 1 – Shape of the plug       17         Figure B.1 – Radiated emission       17         Figure B.2 – Conducted emission       18         Figure B.3 – Conducted emission       19         Table 1 – Dimensions of the plug       12	D.5	Standards issues	23
D.5.2       EMC evaluation       23         D.5.3       EMC class       23         D.5.4       Safety evaluation       23         D.5.5       LPS requirements       23         D.5.6       Plug       23         D.5.7       Marking of electrical ratings on PC       23         D.5.6       Other issues       23         D.5.7       Marking of electrical ratings on PC       23         D.6       Other issues       24         Annex E (informative)       Electrical specification       25         E.1       DC output load condition and voltage regulation       25         E.2       Over-current protection       26         Bibliography       27       27         Figure 1 – Shape of the plug       12         Figure B.1 – Radiated emission       17         Figure B.2 – Conducted emission       18         Figure B.3 – Conducted emission       19         Table 1 – Ormensions of the plug       12	D.5.1	Environments	23
D.5.3       EMC class       23         D.5.4       Safety evaluation       23         D.5.5       LPS requirements       23         D.5.6       Plug       23         D.5.7       Marking of electrical ratings on PC       23         D.6       Other issues       23         D.6       Other issues       23         D.6       Other issues       24         Annex E (informative)       Electrical specification       25         E.1       DC output load condition and voltage regulation       25         E.2       Over-current protection       26         Bibliography       27       27         Figure 1 – Shape of the plug       12         Figure B.1 – Radiated emission       17         Figure B.2 – Conducted emission       18         Figure B.3 – Conducted emission       19         Tablet – Dimensions of the plug       12	D.5.2	EMC evaluation	23
D.5.4       Safety evaluation       23         D.5.5       LPS requirements       23         D.5.6       Plug       23         D.5.7       Marking of electrical ratings on PC       23         D.6       Other issues       24         Annex E (informative)       Electrical specification       25         E.1       DC output load condition and voltage regulation       25         E.2       Over-current protection       26         Bibliography       27         Figure 1 – Shape of the plug       12         Figure 8.1 – Radiated emission       17         Figure B.2 – Conducted emission       18         Figure B.3 – Conducted emission       19         Table 1 – Dimensions of the plug       12	D.5.3	EMC class	23
D.5.5LPS requirements23D.5.6Plug23D.5.7Marking of electrical ratings on PC23D.6Other issues24Annex E (informative)Electrical specification25E.1DC output load condition and voltage regulation25E.2Over-current protection26Bibliography27Figure 1 – Shape of the plug12Figure B.1 – Radiated emission17Figure B.2 – Conducted emission18Figure B.3 – Conducted emission19Table 1 – Dimensions of the plug12	D.5.4	Safety evaluation	23
D.5.6Plug23D.5.7Marking of electrical ratings on PC23D.6Other issues24Annex E (informative)Electrical specification25E.1DC output load condition and voltage regulation25E.2Over-current protection26Bibliography27Figure 1 – Shape of the plug12Figure B.1 – Radiated emission17Figure B.2 – Conducted emission18Figure B.3 – Conducted emission19Table 1 – Dimensions of the plug12	D.5.5	LPS requirements	23
D.5.7       Marking of electrical ratings on PC	D.5.6	Plug	23
D.6Other issues24Annex E (informative)Electrical specification25E.1DC output load condition and voltage regulation25E.2Over-current protection26Bibliography27Figure 1 – Shape of the plug12Figure B.1 – Radiated emission17Figure B.2 – Conducted emission18Figure B.3 – Conducted emission19Table 1 – Dimensions of the plug12	D.5.7	Marking of electrical ratings on PC	23
Annex E (informative)       Electrical specification       25         E.1       DC output load condition and voltage regulation       25         E.2       Over-current protection       26         Bibliography       27         Figure 1 – Shape of the plug       12         Figure B.1 – Radiated emission       17         Figure B.2 – Conducted emission       18         Figure B.3 – Conducted emission       19         Table 1 – Dimensions of the plug       12	D.6	Other issues	24
E.1       DC output load condition and voltage regulation       25         E.2       Over-current protection       26         Bibliography       27         Figure 1 – Shape of the plug       12         Figure B.1 – Radiated emission       17         Figure B.2 – Conducted emission       18         Figure B.3 – Conducted emission       19         Table 1 – Dimensions of the plug       12	Annex E (i	nformative) Electrical specification	25
E.2       Over-current protection       26         Bibliography       27         Figure 1 – Shape of the plug       12         Figure B.1 – Radiated emission       17         Figure B.2 – Conducted emission       18         Figure B.3 – Conducted emission       19         Table 1 – Dimensions of the plug       12	E.1	DC output load condition and voltage regulation	25
Bibliography       27         Figure 1 – Shape of the plug       12         Figure B.1 – Radiated emission       17         Figure B.2 – Conducted emission       18         Figure B.3 – Conducted emission       19         Table 1 – Dimensions of the plug       12	E.2	Over-current protection	26
Figure 1 – Shape of the plug       12         Figure B.1 – Radiated emission       17         Figure B.2 – Conducted emission       18         Figure B.3 – Conducted emission       19         Table 1 – Dimensions of the plug       12	Bibliograph	ıy	27
Figure 1 – Shape of the plug			
Figure B.1 – Radiated emission       17         Figure B.2 – Conducted emission       18         Figure B.3 – Conducted emission       19         Table 1 – Dimensions of the plug       12	Figure 1 –	Shape of the plug	12
Figure B.2 – Conducted emission       18         Figure B.3 – Conducted emission       19         Table 1 – Dimensions of the plug       12	Figure B 1	- Radiated emission	17
Figure B.2 – Conducted emission	Figure D.1		17
Figure B.3 – Conducted emission		- Conducted emission	18
Table 1 – Dimensions of the plug	Figure B.3	- Conducted emission	19
Table 1 – Dimensions of the plug			
	Table 1 – I	Dimensions of the plug	12
	$\langle \rangle$		

#### INTERNATIONAL ELECTROTECHNICAL COMMISSION

## DC POWER SUPPLY FOR NOTEBOOK COMPUTERS

## FOREWORD

- 1) The International Electrotechnical Commission (IEC) is a worldwide organization for standardization comprising all national electrotechnical committees (IEC National Committees). The object of IEC is to promote international co-operation on all questions concerning standardization in the electrical and electronic fields. To this end and in addition to other activities, IEC publishes International Standards, Technical Specifications, Technical Reports, Publicly Available Specifications (PAS) and Guides (hereafter referred to as "IEC Publication(s)"). Their preparation is entrusted to technical committees; any IEC National Committee interested in the subject dealt with may participate in this preparatory work. International, governmental and non-governmental organizations liaising with the IEC also participate in this preparation. IEC collaborates closely with the International Organization for Standardization (ISO) in accordance with conditions determined by agreement between the two organizations.
- The formal decisions or agreements of IEC on technical matters express, as nearly as possible, an international consensus of opinion on the relevant subjects since each technical committee has representation from all interested IEC National Committees.
- 3) IEC Publications have the form of recommendations for international use and are accepted by IEC National Committees in that sense. While all reasonable efforts are made to ensure that the technical content of IEC Publications is accurate, IEC cannot be held responsible for the way in which they are used or for any misinterpretation by any end user.
- 4) In order to promote international uniformity, IEC National Committees undertake to apply IEC Publications transparently to the maximum extent possible in their national and regional publications. Any divergence between any IEC Publication and the corresponding national or regional publication shall be clearly indicated in the latter.
- 5) IEC itself does not provide any attestation of conformity. Independent certification bodies provide conformity assessment services and, in some areas, access to IEC marks of conformity. IEC is not responsible for any services carried out by independent certification bodies.
- 6) All users should ensure that they have the latest edition of this publication.
- 7) No liability shall attach to IEC or its directors, employees, servants or agents including individual experts and members of its technical committees and IEC National Committees for any personal injury, property damage or other damage of any nature whatsoever, whether direct or indirect or for costs (including legal fees) and expenses arising out of the publication, use of, or reliance upon, this IEC Publication or any other IEC Publications.
- 8) Attention is drawn to the Normative references cited in this publication. Use of the referenced publications is indispensable for the correct application of this publication.
- Attention is drawn to the possibility that some of the elements of this IEC Publication may be the subject of patent rights. IEC shall not be held responsible for identifying any or all such patent rights.

The main task of IEC technical committees is to prepare International Standards. In exceptional circumstances, a technical committee may propose the publication of a technical specification when

- the required support cannot be obtained for the publication of an International Standard, despite repeated efforts, or
- the subject is still under technical development or where, for any other reason, there is the future but no immediate possibility of an agreement on an International Standard.

Technical specifications are subject to review within three years of publication to decide whether they can be transformed into International Standards.

IEC/TS 62700, which is a technical specification, has been prepared by technical area 14: Interfaces and methods of measurement for personal computing equipment of IEC technical committee 100: Audio, video and multimedia systems and equipment.

The text of this technical specification is based on the following documents:

Enquiry draft	Report on voting
100/2170/DTS	100/2231/RVC

Full information on the voting for the approval of this technical specification can be found in the report on voting indicated in the above table.

This publication has been drafted in accordance with the ISO/IEC Directives, Part 2.

The committee has decided that the contents of this publication will remain unchanged until the stability date indicated on the IEC web site under "http://webstore.iec.ch" in the data related to the specific publication. At this date, the publication will be

• transformed into an International Standard,

forstake

- reconfirmed,
- withdrawn,
- replaced by a revised edition, or
- amended.

IMPORTANT – The 'colour inside' logo on the cover page of this publication indicates that it contains colours which are considered to be useful for the correct understanding of its contents. Users should therefore print this document using a colour printer.

#### INTRODUCTION

In consideration of global discussion on reducing e-waste and improving re-usability of power supplies, this Technical Specification addresses the common electro- mechanical characteristics for AC adapters used with a specified array of notebook computers.

In the current market, hundreds of millions of notebook computers are shipped every year with AC adapters which can typically be shared between generations of OEM notebook computers. A wide range of notebook computers are designed to meet unique market requirements and specific purposes. Each AC adapter is tuned and designed to optimally satisfy the requirements and specifications of the target notebook computers.

Specific combinations of OEM supplied AC adapters and notebook computers are tested and certified as a system in compliance with existing regulations and standards. Failing combinations are not shipped by the OEM to the consumer. This approach promotes consumer satisfaction, safety, and product reliability, while reducing the encroachment of poorly designed or manufactured aftermarket substitutes which may affect the operation of the notebook computer in compliance with regulatory requirements. Additionally, arbitrary combinations of AC adapters and notebook computers have been known to present functional and regulatory safety and EMC compliance issues for the notebook computer. These risks should be considered in any development or adoption of specifications for common AC adapters.

The objective of a common DC power supply is to support global interoperability of adapters for a specific range of notebook computers. This Technical Specification describes design considerations for the common adapters and identifies technical areas that require further development for interoperability with existing notebook computer technologies. The open technical and regulatory compliance issues identified within this Technical Specification which affect both AC adapters and the host notebook computers should be resolved before this specification can be considered as a normative within other standards or regulatory policies and before IEC standardization of the subject matter can be completed.

This Technical Specification also identifies important considerations required to maintain the high standard of safety, compliance and performance expected by users of notebook computers and global regulatory agencies.

The development of this Technical Specification is described in Annex A. Annexes C, D and E describe additional important areas which are required to be resolved in further standardization work.

The objective for future IEC standardization work will be to complete the development of the technical specifications which incorporates considerations for consumer safety, product reliability, system performance, regulatory compliance and technical innovations.

## DC POWER SUPPLY FOR NOTEBOOK COMPUTERS

#### 1 Scope

This Technical Specification states the minimum requirements for DC power supply for notebook computers. Specifically, it gives

- an electrical specification (performance characteristics),
- an ID pin method,
- a connector for DC power output.

The no-load power and power efficiency are outside the scope of this Technical Specification.

Note that safety requirements are covered by IEC 60950-1 and EMC requirements are covered by CISPR 22 and CISPR 24. CISPR 32 may be used in place of CISPR 22 for this purpose. These requirements are neither re-stated nor challenged by this Technical Specification but the designer should give due consideration to the performance of the power supply when used with a compatible notebook computer.

NOTE Applications for use in aerospace, military, medical, or smart grid are not addressed in this Technical Specification.

#### 2 Normative references

The following documents, in whole or in part, are normatively referenced in this document and are indispensable for its application. For dated references, only the edition cited applies. For undated references, the latest edition of the referenced document (including any amendments) applies.

IEC 60950-1:2005, Information technology equipment – Safety – Part 1: General requirements

Amendment 1:2009 Amendment 2:2013

IEC 61076-2-102, Connectors for electronic equipment – Part 2-102: Circular connectors with assessed quality – Detail specification for plugs and jacks for external low voltage power supply

IEC 61204:1993, Low-voltage power supply devices, d.c. output – Performance characteristics

Amendment 1:2001

CISPR 22, Information technology equipment – Radio disturbance characteristics – Limits and methods of measurement

CISPR 24, Information technology equipment - Immunity characteristics - Limits and methods of measurement

CISPR 32, Electromagnetic compatibility of multimedia equipment - Emission requirements

with the state of the second s